



THORN EMI

Installation and Wiring Instructions for 2D 28W ADAPTOR 2D A28

DESCRIPTION

The 2D 28 watt adaptor and lamp is a direct replacement for GLS lamps in ceiling-mounted fittings, table lamps and wall standards. It is not suitable for use in pendant fittings unless a strain relief flexible cable is used.

IMPORTANT

Ensure that the fitting is turned off before attempting to fit adaptor.

FIXING DETAILS

(1) Ceiling-mounted fittings.

Check that sufficient space is available inside the lighting fitting to accommodate the lamp. Check that the lighting fitting and wiring are able to support the adaptor and lamp weight. Frayed or old wiring must be replaced, as should any plastic lampholder parts showing signs of cracking.

Fit the lamp into the adaptor.

Fit the adaptor/lamp combination into the BC lampholder.

(2) Table lamps and wall standards.

Check that sufficient space is available inside the lighting fitting to accommodate the lamp. (In some cases it may be necessary to bend the shade support arms).

Fit the lamp into the adaptor.

Fit the adaptor/lamp combination into the BC lampholder.

OPERATING CONDITIONS

Suitable for use in warm dry atmospheres (IP 20 rating).

COUNTRY OF ORIGIN

Made in U.K.

CHANGE OF SPECIFICATION

The right is reserved to change specification without prior notification or public announcement.

IMPORTANT NOTES

(1) Ensure that the rated voltage of the luminaire is compatible with the mains supply.

(2) Ensure that the BC lampholder is able to support the adaptor and lamp weight.

SERVICING AND DISPOSAL

Servicing, eg cleaning, lamp replacement, should only be carried out after the luminaire has been disconnected from the electricity supply.

Cleaning should be carried out at regular intervals to ensure that dirt does not accumulate to an extent that will impair the thermal safety of the luminaire. Failed lamps should be replaced as soon as practicable by lamps of the same type.

These lamps should be broken in a container.

Precautions should be taken against flying glass or other fragments. The operation should be carried out outdoors (or in a well ventilated area).

RANGE DETAILS

Cat. No.

2D A28

Adaptor c/w 2D 28 watts lamp.
(240v B.C.)

LAMP TYPES

1 x 2D 28 watts

STANDARD DOMESTIC B.C.
LAMPHOLDER FITMENT
(Not supplied)



ADAPTOR

