



# DISCHARGE LAMP CONTROL GEAR

## HIGH PRESSURE MERCURY

## BALLASTS

### TYPES: MB, MBF MBFR

Lamp Watts	Voltage 50Hz	Ballast Cat No	PFC Capacitor Cat No*	Cross Section mm W x H	Overall Length mm	Fixing Centres mm	Ignitor
80	220 - 240	Z1641P	Z16749	60 x 48	165	152	not required
125	220 - 240	Z1651P	Z16759	64 x 48	165	152	not required
250	220 - 240	Z1661P	Z17138	107 x 109	133	113 x 76	not required
400	220 - 240	Z1681P	Z17158	107 x 109	133	113 x 76	not required
700	220 - 240	Z1684P	Z17869	107 x 109	166	146 x 76	not required
1000	220 - 240	Z1685P	2 x Z17168	107 x 109	166	146 x 76	not required
1000	380 - 440	Z1686P	Z17529	107 x 109	166	146 x 76	not required
<b>TYPE MBI</b>							
400 Green or Blue	220 - 240	Z1646P	Z17869 F8058T Stabiliser	98 x 81	150	135 x 76	not required
2000 White	380 - 440	Z1648P	2 x Z1754	150 x 126	220	180 x 125	OSH 15

## HIGH PRESSURE SODIUM

70	220 - 240	Z1628P	Z16759	64 x 48	165	152	OSL 30
120	220 - 240	Z1656P	Z17128	76 x 54	165	152	OSL 30
150	220 - 240	Z1615P	Z17158	76 x 54	165	152	OSH 30
250	220 - 240	Z1883P	Z17869	107 x 109	133	113 x 76	OSH 30
400	220 - 240	Z1885P	Z17589	107 x 109	133	113 x 76	OSH 30
600	380 - 440	Z1889P	Z17549	107 x 109	166	146 x 76	OSH 15
600	220 - 240	Z1890P	2 x Z17869	107 x 109	166	146 x 76	OSH 30
1000	380 - 440	Z1609P	2 x Z17529	150 x 126	220	180 x 125	OSH 15
1000	220 - 240	Z1608	4 x Z17168	150 x 126	220	180 x 125	OSH 30

## SUPER SOX

35/55	220 + 240	Z1612P	Z17138	76 x 59	224	210	not required
35/55	240	Z1610P	Z17138	76 x 59	224	210	not required
35/55	240	†Z1616P	Z17579	53 x 66	159	146	not required
90	220 + 240	Z1622P	Z17168	99 x 74	178	162	not required
90	240	Z1621P	Z17168	99 x 74	178	162	not required
135/180	240	Z1633P	Z17529	107 x 109	166	146 x 76	not required
135/180	220 + 240	Z1634P	Z17529	107 x 109	166	146 x 76	not required

\* Includes mounting clip

† Low loss type with integral ignitor