Mannas

TYPE VEN-O-SET

The Ven-O-Set miniature time switch is the simplest device available for the automatic control of one light.

Being a self-contained portable unit, it may be plugged into any bayonet fitting lampholder and the lamp fitted to the socket of the time switch. The dial will rotate once in 24 hours continually, as long as the unit remains switched on.

Two pointers, one for the ON and one for the OFF control the switching and they are set by simply moving them round the dial to the time chosen. No tools are required.

The operation of the dial may be by-passed by operating the ON or OFF manual switch which is incorporated.



SPECIFICATION

DIAL 24-hour dial designed for easy setting, arranged to switch ON and OFF once per day.

Minimum ON period $1\frac{1}{2}$ hours. Maximum ON period $22\frac{1}{2}$ hours. CASE Moulded ivory or black plastic with transparent hinged front cover.

RATING 1 amp., 100/120 or 200/250 volts 50 cycles AC only.

WEIGHT 13 oz. approximately.

DIMENSIONS $2\frac{1}{8}$ " wide \times $2\frac{3}{8}$ " deep \times $5\frac{5}{8}$ " high. (5.4 cm. \times 6.04 cm. \times 14.3 cm.).



VENNER LIMITED · KINGSTON BY-PASS · NEW MALDEN · SURREY · MALden 2442